

# ONVIF™ Access Control Service Specification

Version 18.06  
June 2018



© 2008-2018 by ONVIF: Open Network Video Interface Forum Inc. All rights reserved. Recipients of this document may copy, distribute, publish, or display this document so long as this copyright notice, license and disclaimer are retained with all copies of the document. No license is granted to modify this document.

THIS DOCUMENT IS PROVIDED "AS IS," AND THE CORPORATION AND ITS MEMBERS AND THEIR AFFILIATES, MAKE NO REPRESENTATIONS OR WARRANTIES, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO, WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, NON-INFRINGEMENT, OR TITLE; THAT THE CONTENTS OF THIS DOCUMENT ARE SUITABLE FOR ANY PURPOSE; OR THAT THE IMPLEMENTATION OF SUCH CONTENTS WILL NOT INFRINGE ANY PATENTS, COPYRIGHTS, TRADEMARKS OR OTHER RIGHTS.

IN NO EVENT WILL THE CORPORATION OR ITS MEMBERS OR THEIR AFFILIATES BE LIABLE FOR ANY DIRECT, INDIRECT, SPECIAL, INCIDENTAL, PUNITIVE OR CONSEQUENTIAL DAMAGES, ARISING OUT OF OR RELATING TO ANY USE OR DISTRIBUTION OF THIS DOCUMENT, WHETHER OR NOT (1) THE CORPORATION, MEMBERS OR THEIR AFFILIATES HAVE BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES, OR (2) SUCH DAMAGES WERE REASONABLY FORESEEABLE, AND ARISING OUT OF OR RELATING TO ANY USE OR DISTRIBUTION OF THIS DOCUMENT. THE FOREGOING DISCLAIMER AND LIMITATION ON LIABILITY DO NOT APPLY TO, INVALIDATE, OR LIMIT REPRESENTATIONS AND WARRANTIES MADE BY THE MEMBERS AND THEIR RESPECTIVE AFFILIATES TO THE CORPORATION AND OTHER MEMBERS IN CERTAIN WRITTEN POLICIES OF THE CORPORATION.

## CONTENTS

<b>1</b>	<b>Scope</b>	<b>6</b>
1.1	General.....	6
1.2	Conventions .....	6
1.3	Namespaces .....	6
<b>2</b>	<b>Normative references</b>	<b>6</b>
<b>3</b>	<b>Terms, definitions and abbreviations</b>	<b>7</b>
3.1	Terms and definitions.....	7
3.2	Abbreviations .....	8
<b>4</b>	<b>Overview</b>	<b>9</b>
<b>5</b>	<b>Access control</b>	<b>10</b>
5.1	Service capabilities .....	10
5.1.1	General .....	10
5.1.2	Data structures.....	10
5.1.3	GetServiceCapabilities command.....	10
5.2	Access point information .....	11
5.2.1	Data structures.....	11
5.2.2	GetAccessPointInfo command .....	12
5.2.3	GetAccessPointInfoList command.....	13
5.2.4	GetAccessPoints command.....	14
5.2.5	GetAccessPointList command.....	14
5.2.6	CreateAccessPoint command .....	15
5.2.7	SetAccessPoint command.....	16
5.2.8	ModifyAccessPoint command.....	17
5.2.9	DeleteAccessPoint command.....	17
5.2.10	SetAccessPointAuthenticationProfile command .....	18
5.2.11	DeleteAccessPointAuthenticationProfile command .....	18
5.3	Area Information.....	19
5.3.1	Data structures.....	19
5.3.2	GetAreaInfo command.....	19
5.3.3	GetAreaInfoList command .....	20
5.3.4	GetAreas command.....	21
5.3.5	GetAreaList command .....	21
5.3.6	CreateArea command.....	22
5.3.7	SetArea command .....	23
5.3.8	ModifyArea command.....	24
5.3.9	DeleteArea command .....	24
5.4	Access point status .....	25
5.4.1	General .....	25
5.4.2	Data structures.....	25
5.4.3	GetAccessPointSize command .....	25
5.5	Access control commands .....	26
5.5.1	General .....	26
5.5.2	Data structures.....	26
5.5.3	EnableAccessPoint command .....	26
5.5.4	DisableAccessPoint command .....	26
5.5.5	ExternalAuthorization command.....	27
<b>6</b>	<b>Notification topics</b>	<b>28</b>
6.1	General.....	28
6.2	Event overview .....	28
6.2.1	General .....	28
6.2.2	General transaction event layout.....	28

- 6.3 Access granted .....29
  - 6.3.1 General .....29
  - 6.3.2 Anonymous .....29
  - 6.3.3 Credential.....29
- 6.4 Access taken .....30
  - 6.4.1 General .....30
  - 6.4.2 Anonymous .....30
  - 6.4.3 Credential.....30
- 6.5 Access not taken .....30
  - 6.5.1 General .....30
  - 6.5.2 Anonymous .....30
  - 6.5.3 Credential.....31
- 6.6 Access denied .....31
  - 6.6.1 General .....31
  - 6.6.2 Anonymous .....32
  - 6.6.3 Credential.....33
  - 6.6.4 CredentialNotFound.....33
- 6.7 Duress .....34
- 6.8 External authorization .....34
  - 6.8.1 General .....34
  - 6.8.2 Anonymous .....34
  - 6.8.3 Credential.....35
  - 6.8.4 Timeout .....35
  - 6.8.5 Example .....35
- 6.9 Status changes .....35
  - 6.9.1 General .....35
  - 6.9.2 Access point.....36
  - 6.9.3 Security level.....36
- 6.10 Configuration changes .....36
  - 6.10.1 General.....36
  - 6.10.2 Access Point.....36
  - 6.10.3 Area .....37
- Annex A. Revision History .....38**

## Contributors

ASSA ABLOY	Patrik Björling Rygert
ASSA ABLOY	Mattias Rengstedt
Axis Communications AB	Johan Adolfsson
Axis Communications AB	Marcus Johansson
Axis Communications AB	Robert Rosengren
Axis Communications AB	Derek Wang
Axis Communications AB	Emil Selinder
AxxonSoft	Yuri Timenkov
Bosch	Mohane Caliaperoumal
Bosch	Dirk Schreiber
Hirsch Electronics/ Identive Group	Rob Zivney
Honeywell	Marine Drive
Honeywell	Neelendra Bhandari
Honeywell	Uvaraj Thangarajan
Honeywell	Vinay Ghule
PACOM	Eugene Scully
PACOM	Steve Barton
Schneider Electric	Mike Berube
Siemens AG	Klaus Baumgartner
Siemens AG	Suresh Raman
Siemens AG	Suresh Krishnamurthy

## 1 Scope

### 1.1 General

This specification defines the web service interface for interaction with physical access control systems. This includes discovering components and their logical composition and controlling them.

Supplementary dedicated services such as low-level door control, schedule management will be defined in separate documents.

Web service usage and common ONVIF functionality are outside of the scope of this document. Please refer to [ONVIF Core Specification] for more information.

### 1.2 Conventions

The key words “shall”, “shall not”, “should”, “should not”, “may”, “need not”, “can”, “cannot” in this specification are to be interpreted as described in Annex H of [ISO/IEC Directives].

### 1.3 Namespaces

This document references the following namespaces:

**Table 1: Referenced namespaces (with prefix)**

Prefix	Namespace URI
env	<a href="http://www.w3.org/2003/05/soap-envelope">http://www.w3.org/2003/05/soap-envelope</a>
ter	<a href="http://www.onvif.org/ver10/error">http://www.onvif.org/ver10/error</a>
xs	<a href="http://www.w3.org/2001/XMLSchema">http://www.w3.org/2001/XMLSchema</a>
tt	<a href="http://www.onvif.org/ver10/schema">http://www.onvif.org/ver10/schema</a>
pt	<a href="http://www.onvif.org/ver10/pacs">http://www.onvif.org/ver10/pacs</a>
tns1	<a href="http://www.onvif.org/ver10/topics">http://www.onvif.org/ver10/topics</a>
tmd	<a href="http://www.onvif.org/ver10/deviceIO/wsd">http://www.onvif.org/ver10/deviceIO/wsd</a>
tdc	<a href="http://www.onvif.org/ver10/doorcontrol/wsd">http://www.onvif.org/ver10/doorcontrol/wsd</a>
tac	<a href="http://www.onvif.org/ver10/accesscontrol/wsd">http://www.onvif.org/ver10/accesscontrol/wsd</a>

## 2 Normative references

The following documents, in whole or in part, are normatively referenced in this document and are indispensable for its application. For dated references, only the edition cited applies. For undated references, the latest edition of the referenced document (including any amendments) applies.

ONVIF Core Specification

<<http://www.onvif.org/specs/core/ONVIF-Core-Specification.pdf>>

ONVIF PACS Architecture and Design Considerations

<<https://www.onvif.org/specs/wp/ONVIF-PACS-Architecture-and-Design-Considerations.pdf>>

ONVIF Door Control Service Specification

<<http://www.onvif.org/specs/srv/door/ONVIF-DoorControl-Service-Spec.pdf>>

ONVIF Authentication Behavior Service Specification

<<http://www.onvif.org/specs/srv/auth/ONVIF-AuthenticationBehavior-Service-Spec.pdf>>

ISO/IEC Directives, *ISO/IEC Directives Part 2, Principles and rules for the structure and drafting of ISO and IEC documents, Edition 7.0, May 2016*

<[http://www.iec.ch/members\\_experts/refdocs/iec/isoiecdirectives-2%7Bed7.0%7Den.pdf](http://www.iec.ch/members_experts/refdocs/iec/isoiecdirectives-2%7Bed7.0%7Den.pdf)>

### 3 Terms, definitions and abbreviations

#### 3.1 Terms and definitions

For the purposes of this document, the following terms and definitions apply.

<b>Access Control Service</b>	A device implementing the ONVIF Access Control Service Specification (this specification).
<b>Access Control Unit</b>	<p>Part of an access control system that interfaces with readers, locking devices and sensing devices, making a decision to grant or deny access through a portal.</p> <p>From an ONVIF perspective, it is a device or system implementing at least the access control service. Often, it is a microprocessor-based circuit board that manages access to a secure area. The access control unit receives information that it uses to determine through which doors and at what times credential holders are granted access to secure areas. Based on that information, the access control unit can lock/unlock doors, sound alarms, and communicate status to a host computer.</p>
<b>Access Point</b>	A logical composition of a physical door, reader(s) and/or a request-to-exit device controlling access in one direction.
<b>Access Point Disable</b>	If an access point is disabled, it will not be considered in the decision-making process and no commands will be issued from that access point to the door configured for that access point. When an access point is disabled, the associated reader(s) may or may not be disabled or shut down. Clients may still be able to command the door control unit to control associated door even though that door is also referenced by a disabled access point.
<b>Area</b>	A protected or controlled area defined by a physical boundary, through which passage is controlled by means of one or more doors.
<b>Client</b>	An ONVIF service requester. A typical ONVIF network system may have multiple clients that handle device configuration and device management operations for numerous devices. A device providing services may also act as a client to other devices.
<b>Credential</b>	A logical object holding related credential identifiers for a credential holder. E.g. if a PIN is associated with a specific credential number, then both of these identifiers are stored in one credential. Note that the PIN is normally not stored in the physical credential.
<b>Credential Holder</b>	A person holding a credential.
<b>Credential Identifier</b>	Information either memorized or held within a physical credential. Could be a credential number, PIN, biometric information, etc., that can be validated in an access point.
<b>Credential Number</b>	A sequence of bytes uniquely identifying a physical credential at an access point.
<b>Device</b>	An ONVIF service provider implementing one or more ONVIF services. E.g. an access control unit or a door control unit.
<b>Door</b>	A physical door, barrier, turnstile, etc. which can be controlled remotely and restricts access between two areas. A door is usually equipped with an electronic lock and a door monitor.
<b>Door Control Service</b>	A device implementing [ONVIF Door Control Service Specification].

<b>Door Control Unit</b>	From an ONVIF perspective, it is a device or system implementing at least the door control service, but not the access control service. Often, it is a microprocessor-based circuit board that manages door locks and/or door monitors for one or more doors.
<b>Door Lock</b>	A device that secures a door to prevent access, except when explicitly allowed by the access control system. Lock types include electromagnetic, electric strike, etc.
<b>Door Monitor</b>	Electrical component used to monitor the open or closed status of a door, or locked/unlocked status of a locking device, or the secure/unsecure status of an electromagnetic lock or armature plate. Also known as door contact sensor.
<b>Duress</b>	Forcing a person to provide access to a secure area against that person's wishes.
<b>Peripheral Device</b>	An I/O device physically wired to the access control unit. Some peripheral devices are associated with an access point (e.g. reader or request-to-exit button), and some are associated with a door (e.g. door monitor).
<b>Physical Credential</b>	Portable device containing a readable unique credential number that can be associated with the credential holder's data and access rules stored within the electronic access control system. Examples are card, key, fob, smart phone, etc.
<b>Reader</b>	Device for the input of credentials. Examples include card readers, biometric readers, etc.
<b>Request-to-Exit Device</b>	A peripheral device associated with an access point used to initiate free exit.

### 3.2 Abbreviations

<b>ACMS</b>	Access Control Management System
<b>BMS</b>	Building Management System
<b>HTTP</b>	Hypertext Transfer Protocol
<b>PACS</b>	Physical Access Control System
<b>PSIM</b>	Physical Security Information Management
<b>REX</b>	Request-to-Exit
<b>TLS</b>	Transport Layer Security
<b>VMS</b>	Video Management System



## 4 Overview

Physical access control is all about who (credential holders) can access what (areas), when (schedules) and how (security levels).


Access points represents the sides of a door, and are the points of access that you need to pass to get to a protected area. An access point is typically equipped with a reader or a request-to-exit device controlling access from one area to another area.

An access point may also be associated with an authentication profile that defines how (i.e. which security level) to get access to an area and when (defined by a schedule). A typical example is an access point that requires card during day time and card plus PIN code during night time.

Every access point offers different capabilities, such as support for duress or what security levels are supported.

The access control service offers commands to manage the access points and areas, to retrieve status information and to control access point instances.

The following picture shows the main data structures involved in the access control service:



**Figure 1: Main data structures in the access control service**

## 5 Access control

### 5.1 Service capabilities

#### 5.1.1 General

A device shall provide service capabilities in two ways:

1. With the GetServices method of Device service when IncludeCapability is true. Please refer to [ONVIF Core Specification] for more details.
2. With the GetServiceCapabilities method.

#### 5.1.2 Data structures

##### 5.1.2.1 ServiceCapabilities

The service capabilities reflect optional functionality of a service. The information is static and does not change during device operation. The following capabilities are available:

- **MaxLimit**  
The maximum number of entries returned by a single Get<Entity>List or Get<Entity> request. The device shall never return more than this number of entities in a single response.
- **MaxAccessPoints**  
Indicates the maximum number of access points supported by the device.
- **MaxAreas**  
Indicates the maximum number of areas supported by the device.
- **ClientSuppliedTokenSupported**  
Indicates that the client is allowed to supply the token when creating access points and areas. To enable the use of the commands SetAccessPoint and SetArea, the value must be set to true.

##### 5.1.3 GetServiceCapabilities command

This operation returns the capabilities of the access control service.

A device which provides the access control service shall implement this method.

**Table 2 – GetServiceCapabilities command**

GetServiceCapabilities		Access Class: PRE_AUTH
Message name	Description	
GetServiceCapabilitiesRequest	<i>This message shall be empty</i>	
GetServiceCapabilitiesResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>• <i>"Capabilities": The capability response message contains the requested access control service capabilities using a hierarchical XML capability structure.</i></li> </ul> <p>tac:ServiceCapabilities <b>Capabilities [1][1]</b></p>	

## 5.2 Access point information

### 5.2.1 Data structures

#### 5.2.1.1 AccessPointInfo

The AccessPointInfo structure contains basic information about an access point instance. An access point defines an entity a credential can be granted or denied access to. The AccessPointInfo structure provides basic information on how access is controlled in one direction for a door (from which area to which area).

Multiple access points may cover the same door. A typical case is one access point for entry and another for exit, both referencing the same door.

The device shall provide the following fields for each access point instance:

- **token**  
A service-unique identifier of the access point.
- **Name**  
A user readable name. It shall be up to 64 characters.
- **Entity**  
Reference to the entity used to control access; the entity type may be specified by the optional EntityType field explained below but is typically a door.
- **Capabilities**  
The capabilities for the access point.

To provide more information, the device may include the following optional fields:

- **Description**  
Optional user readable description for the access point. It shall be up to 1024 characters.
- **AreaFrom**  
Optional reference to the area from which access is requested.
- **AreaTo**  
Optional reference to the area to which access is requested.
- **EntityType**  
Optional entity type; if missing, a Door type as defined by [ONVIF Door Control Service Specification] should be assumed. This can also be represented by the QName value “tdc:Door” – where tdc is the namespace of the door control service: “<http://www.onvif.org/ver10/doorcontrol/wsd>”. This field is provided for future extensions; it will allow an access point being extended to cover entity types other than doors as well.

### 5.2.1.2 AccessPoint

The AccessPoint structure shall include all properties of the AccessPointInfo structure, and optionally a reference to an authentication profile instance.

The device may provide the following optional fields for each access point instance:

- **AuthenticationProfileToken**

A reference to an authentication profile which defines the authentication behavior of the access point.

During the installation phase of an access control system, the authentication behavior is typically not defined, but the list of supported security levels are (see section 5.2.1.3). At a later stage, someone (e.g. a security officer) will define the authentication behavior for the access point by calling the SetAccessPointAuthenticationProfile command (see section 5.2.10).

### 5.2.1.3 AccessPointCapabilities

The access point capabilities reflect optional functionality of a particular physical entity. Different access point instances may have different set of capabilities. This information may change during device operation, e.g. if hardware settings are changed. The following capabilities are available:

- **DisableAccessPoint**

Indicates whether or not this access point instance supports the EnableAccessPoint and DisableAccessPoint commands.

- **Duress**

Indicates whether or not this access point instance supports generation of duress events.

- **AnonymousAccess**

Indicates whether or not this access point has a REX switch or other input that allows anonymous access.

- **AccessTaken**

Indicates whether or not this access point instance supports generation of AccessTaken and AccessNotTaken events. If AnonymousAccess and AccessTaken are both true, it indicates that the Anonymous versions of AccessTaken and AccessNotTaken are supported.

- **ExternalAuthorization**

Indicates whether or not this access point instance supports the ExternalAuthorization operation and the generation of Request events. If AnonymousAccess and ExternalAuthorization are both true, it indicates that the Anonymous version is supported as well.

- **SupportedSecurityLevels**

A list of security level tokens that this access point supports. See [ONVIF Authentication Behavior Service Specification].

### 5.2.2 GetAccessPointInfo command

This operation requests a list of AccessPointInfo items matching the given tokens.

The device shall ignore tokens it cannot resolve and shall return an empty list if there are no items matching the specified tokens. The device shall not return a fault in this case.

If the number of requested items is greater than MaxLimit, a TooManyItems fault shall be returned.

**Table 3 – GetAccessPointInfo command**

<b>GetAccessPointInfo</b>		Access Class: READ_SYSTEM
<b>Message name</b>	<b>Description</b>	
GetAccessPointInfoRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Token": Tokens of AccessPointInfo items to get.</li> </ul> pt:ReferenceToken <b>Token [1][unbounded]</b>	
GetAccessPointInfoResponse	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"AccessPointInfo": List of AccessPointInfo items.</li> </ul> tac:AccessPointInfo <b>AccessPointInfo [0][unbounded]</b>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgs ter:TooManyItems	<i>Too many items were requested, see MaxLimit capability.</i>	

### 5.2.3 GetAccessPointInfoList command

This operation requests a list of all AccessPointInfo items provided by the device.

A call to this method shall return a StartReference when not all data is returned and more data is available. The reference shall be valid for retrieving the next set of data. Please refer to section 4.8.3 in [ONVIF PACS Architecture and Design Considerations] for more details.

The number of items returned shall not be greater than the Limit parameter.

**Table 4 – GetAccessPointInfoList command**

<b>GetAccessPointInfoList</b>		Access Class: READ_SYSTEM
<b>Message name</b>	<b>Description</b>	
GetAccessPointInfoListRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Limit": Maximum number of entries to return. If Limit is omitted or if the value of Limit is higher than what the device supports, then the device shall return its maximum amount of entries.</li> <li>"StartReference": Start returning entries from this start reference. If not specified, entries shall start from the beginning of the dataset.</li> </ul> xs:int <b>Limit [0][1]</b> xs:string <b>StartReference [0][1]</b>	
GetAccessPointInfoListResponse	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"NextStartReference": StartReference to use in next call to get the following items. If absent, no more items to get.</li> <li>"AccessPointInfo": List of AccessPointInfo items.</li> </ul> xs:string <b>NextStartReference [0][1]</b> tac:AccessPointInfo <b>AccessPointInfo [0][unbounded]</b>	

Fault codes	Description
env:Sender ter:InvalidArgVal ter:InvalidStartReference	<i>StartReference is invalid or has timed out. Client needs to start fetching from the beginning.</i>

#### 5.2.4 GetAccessPoints command

This operation requests a list of AccessPoint items matching the given tokens.

The device shall ignore tokens it cannot resolve and shall return an empty list if there are no items matching the specified tokens. The device shall not return a fault in this case.

If the number of requested items is greater than MaxLimit, a TooManyItems fault shall be returned.

**Table 5 – GetAccessPoints command**

GetAccessPoints		Access Class: READ_SYSTEM
Message name	Description	
GetAccessPointRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Token": Tokens of AccessPoint items to get</li> </ul> pt:ReferenceToken <b>Token [1][unbounded]</b>	
GetAccessPointResponse	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"AccessPoint": List of AccessPoint items.</li> </ul> tac:AccessPoint <b>AccessPoint [0][unbounded]</b>	
Fault codes	Description	
env:Sender ter:InvalidArgs ter:TooManyItems	<i>Too many items were requested, see MaxLimit capability.</i>	

#### 5.2.5 GetAccessPointList command

This operation requests a list of all AccessPoint items provided by the device.

A call to this method shall return a StartReference when not all data is returned and more data is available. The reference shall be valid for retrieving the next set of data. Please refer to section 4.8.3 in [ONVIF PACS Architecture and Design Considerations] for more details.

The number of items returned shall not be greater than the Limit parameter.

Table 6 – GetAccessPointList command

GetAccessPointList		Access Class: READ_SYSTEM
Message name	Description	
GetAccessPointListRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Limit": Maximum number of entries to return. If Limit is omitted or if the value of Limit is higher than what the device supports, then the device shall return its maximum amount of entries.</li> <li>"StartReference": Start returning entries from this start reference. If not specified, entries shall start from the beginning of the dataset.</li> </ul> <p>xs:int <b>Limit</b> [0][1] xs:string <b>StartReference</b> [0][1]</p>	
GetAccessPointListResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"NextStartReference": StartReference to use in next call to get the following items. If absent, no more items to get.</li> <li>"AccessPoint": List of AccessPoint items.</li> </ul> <p>xs:string <b>NextStartReference</b> [0][1] tac:AccessPoint <b>AccessPoint</b> [0][unbounded]</p>	
Fault codes	Description	
env:Sender ter:InvalidArgVal ter:InvalidStartReference	<p><i>StartReference is invalid or has timed out. Client needs to start fetching from the beginning.</i></p>	

### 5.2.6 CreateAccessPoint command

This operation creates the specified access point in the device.

The token field of the AccessPoint structure shall be empty and the device shall allocate a token for the access point. The allocated token shall be returned in the response.

If the client sends any value in the token field, the device shall return InvalidArgVal as a generic fault code.

Table 7 – CreateAccessPoint command

CreateAccessPoint		Access Class: WRITE_SYSTEM
Message name	Description	
CreateAccessPointRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"AccessPoint": AccessPoint item to create</li> </ul> <p>tac:AccessPoint <b>AccessPoint</b> [1][1]</p>	
CreateAccessPointResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Token": Token of created AccessPoint item</li> </ul> <p>pt:ReferenceToken <b>Token</b> [1][1]</p>	

Fault codes	Description
env:Receiver ter:CapabilityViolated ter:MaxAccessPoints	<i>There is not enough space to add new AccessPoint, see the MaxAccessPoints capability</i>
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>

### 5.2.7 SetAccessPoint command

This method is used to synchronize an access point in a client with the device.

If an access point with the specified token does not exist in the device, the access point is created. If an access point with the specified token exists, then the access point is modified.

A call to this method takes an AccessPoint structure as input parameter. The token field of the AccessPoint structure shall not be empty.

A device that signals support for the ClientSuppliedTokenSupported capability shall implement this command.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 8 – SetAccessPoint command**

SetAccessPoint		Access Class: WRITE_SYSTEM
Message name	Description	
SetAccessPointRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li><i>"AccessPoint": AccessPoint item to create or modify</i></li> </ul> tac:AccessPoint <b>AccessPoint [1][1]</b>	
SetAccessPointResponse	<i>This message shall be empty</i>	
Fault codes	Description	
env:Receiver ter:CapabilityViolated ter:ClientSuppliedTokenSupported	<i>The device does not support that the client supplies the token</i>	
env:Receiver ter:CapabilityViolated ter:MaxAccessPoints	<i>There is not enough space to add new AccessPoint, see the MaxAccessPoints capability</i>	
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>	



### 5.2.8 ModifyAccessPoint command

This operation modifies the specified access point.

The token of the access point to modify is specified in the token field of the AccessPoint structure and shall not be empty. All other fields in the structure shall overwrite the fields in the specified access point.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 9 – ModifyAccessPoint command**

<b>ModifyAccessPoint</b>		Access Class: WRITE_SYSTEM
<b>Message name</b>	<b>Description</b>	
ModifyAccessPointRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>• “AccessPoint”: AccessPoint item to modify</li> </ul> tac:AccessPoint <b>AccessPoint [1][1]</b>	
ModifyAccessPointResponse	<i>This message shall be empty</i>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgVal ter:NotFound	<i>Access point token is not found.</i>	
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>	

### 5.2.9 DeleteAccessPoint command

This operation deletes the specified access point.

If it is associated with one or more entities some devices may not be able to delete the access point, and consequently a ReferenceInUse fault shall be generated.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 10 – DeleteAccessPoint command**

<b>DeleteAccessPoint</b>		Access Class: WRITE_SYSTEM
<b>Message name</b>	<b>Description</b>	
DeleteAccessPointRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>• “Token”: Token of AccessPoint item to delete.</li> </ul> pt:ReferenceToken <b>Token [1][1]</b>	
DeleteAccessPointResponse	<i>This message shall be empty</i>	

Fault codes	Description
env:Sender ter:InvalidArgVal ter:NotFound	Access point token is not found.
env:Sender ter:InvalidArgVal ter:ReferenceInUse	Failed to delete, Access point token is in use

**5.2.10 SetAccessPointAuthenticationProfile command**

This operation defines the authentication behavior for an access point.

**Table 11 – SetAccessPointAuthenticationProfile command**

SetAuthenticationProfile		Access Class: ACTUATE
Message name	Description	
SetAccessPointAuthentication-ProfileRequest	This message contains: <ul style="list-style-type: none"> <li>"Token": Token of the AccessPoint</li> <li>"AuthenticationProfileToken": Token of the AuthenticationProfile</li> </ul> pt:ReferenceToken <b>Token [1][1]</b> pt:ReferenceToken <b>AuthenticationProfileToken [1][1]</b>	
SetAccessPointAuthentication-ProfileResponse	This message shall be empty	
Fault codes	Description	
env:Sender ter:InvalidArgVal ter:NotFound	The specified token is not found.	
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	A referred entity token is not found (some devices may not validate referred entities).	
env:Sender ter:CapabilityViolated ter:SupportedSecurityLevels	The referred authentication profile contains security levels that is not supported by this access point.	

**5.2.11 DeleteAccessPointAuthenticationProfile command**

This operation reverts the authentication behavior for an access point to its default behavior.

**Table 12 – DeleteAccessPointAuthenticationProfile command**

SetAuthenticationProfile		Access Class: ACTUATE
Message name	Description	
DeleteAccessPointAuthentication-ProfileRequest	This message contains: <ul style="list-style-type: none"> <li>"Token": Token of the AccessPoint</li> </ul> pt:ReferenceToken <b>Token [1][1]</b>	
DeleteAccessPointAuthentication-ProfileResponse	This message shall be empty	

Fault codes	Description
env:Sender ter:InvalidArgVal ter:NotFound	<i>The specified token is not found.</i>

## 5.3 Area Information

### 5.3.1 Data structures

#### 5.3.1.1 ArealInfo

The ArealInfo structure contains basic information about an area instance.

The device shall provide the following fields for each area instance:

- **token**  
A service-unique identifier of the area.
- **Name**  
User readable name. It shall be up to 64 characters.

To provide more information, the device may include the following optional fields:

- **Description**  
User readable description for the area. It shall be up to 1024 characters.

#### 5.3.1.2 Area

The Area structure shall include all properties of the ArealInfo structure.

Please note that this structure is a placeholder for future attributes.

### 5.3.2 GetArealInfo command

This operation requests a list of ArealInfo items matching the given tokens.

The device shall ignore tokens it cannot resolve and shall return an empty list if there are no items matching the specified tokens. The device shall not return a fault in this case.

If the number of requested items is greater than MaxLimit, a TooManyItems fault shall be returned.

**Table 13 – GetAreaInfo command**

<b>GetAreaInfo</b>		Access Class: READ_SYSTEM
<b>Message name</b>	<b>Description</b>	
GetAreaInfoRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Token": Tokens of AreaInfo items to get.</li> </ul> <p>pt:ReferenceToken <b>Token [1][unbounded]</b></p>	
GetAreaInfoResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"AreaInfo": List of AreaInfo items.</li> </ul> <p>tac:AreaInfo <b>AreaInfo [0][unbounded]</b></p>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgs ter:TooManyItems	<p><i>Too many items were requested, see MaxLimit capability.</i></p>	

### 5.3.3 GetAreaInfoList command

This operation requests a list of all AreaInfo items provided by the device.

A call to this method shall return a StartReference when not all data is returned and more data is available. The reference shall be valid for retrieving the next set of data. Please refer to section 4.8.3 in [ONVIF PACS Architecture and Design Considerations] for more details.

The number of items returned shall not be greater than the Limit parameter.

**Table 14 – GetAreaInfoList command**

<b>GetAreaInfoList</b>		Access Class: READ_SYSTEM
<b>Message name</b>	<b>Description</b>	
GetAreaInfoListRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Limit": Maximum number of entries to return. If Limit is omitted or if the value of Limit is higher than what the device supports, then the device shall return its maximum amount of entries.</li> <li>"StartReference": Start returning entries from this start reference. If not specified, entries shall start from the beginning of the dataset.</li> </ul> <p>xs:int <b>Limit [0][1]</b> xs:string <b>StartReference [0][1]</b></p>	
GetAreaInfoListResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"NextStartReference": StartReference to use in next call to get the following items. If absent, no more items to get.</li> <li>"AreaInfo": List of AreaInfo items.</li> </ul> <p>xs:string <b>NextStartReference [0][1]</b> tac:AreaInfo <b>AreaInfo [0][unbounded]</b></p>	

Fault codes	Description
env:Sender ter:InvalidArgVal ter:InvalidStartReference	<i>StartReference is invalid or has timed out. Client needs to start fetching from the beginning.</i>

#### 5.3.4 GetAreas command

This operation requests a list of Area items matching the given tokens.

The device shall ignore tokens it cannot resolve and shall return an empty list if there are no items matching the specified tokens. The device shall not return a fault in this case.

If the number of requested items is greater than MaxLimit, a TooManyItems fault shall be returned.

**Table 15 – GetAreas command**

GetAreas		Access Class: READ_SYSTEM
Message name	Description	
GetAreasRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Token": Tokens of Area items to get</li> </ul> pt:ReferenceToken <b>Token [1][unbounded]</b>	
GetAreasResponse	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Area": List of Area items.</li> </ul> tac:Area <b>Area [0][unbounded]</b>	
Fault codes	Description	
env:Sender ter:InvalidArgs ter:TooManyItems	<i>Too many items were requested, see MaxLimit capability.</i>	

#### 5.3.5 GetAreaList command

This operation requests a list of all Area items provided by the device.

A call to this method shall return a StartReference when not all data is returned and more data is available. The reference shall be valid for retrieving the next set of data. Please refer to section 4.8.3 in [ONVIF PACS Architecture and Design Considerations] for more details.

The number of items returned shall not be greater than the Limit parameter.

Table 16 – GetAreaList command

<b>GetAreaList</b>		Access Class: READ_SYSTEM
<b>Message name</b>	<b>Description</b>	
GetAreaListRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Limit": Maximum number of entries to return. If Limit is omitted or if the value of Limit is higher than what the device supports, then the device shall return its maximum amount of entries.</li> <li>"StartReference": Start returning entries from this start reference. If not specified, entries shall start from the beginning of the dataset.</li> </ul> <p>xs:int <b>Limit</b> [0][1] xs:string <b>StartReference</b> [0][1]</p>	
GetAreaListResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"NextStartReference": StartReference to use in next call to get the following items. If absent, no more items to get.</li> <li>"Area": List of Area items.</li> </ul> <p>xs:string <b>NextStartReference</b> [0][1] tac:Area <b>Area</b> [0][unbounded]</p>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgVal ter:InvalidStartReference	<p><i>StartReference is invalid or has timed out. Client needs to start fetching from the beginning.</i></p>	

### 5.3.6 CreateArea command

This operation creates the specified area in the device.

The token field of the Area structure shall be empty and the device shall allocate a token for the area. The allocated token shall be returned in the response.

If the client sends any value in the token field, the device shall return InvalidArgVal as a generic fault code.

Table 17 – CreateArea command

<b>CreateArea</b>		Access Class: WRITE_SYSTEM
<b>Message name</b>	<b>Description</b>	
CreateAreaRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Area": Area item to create</li> </ul> <p>tac:Area <b>Area</b> [1][1]</p>	
CreateAreaResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>"Token": Token of created Area item</li> </ul> <p>pt:ReferenceToken <b>Token</b> [1][1]</p>	

Fault codes	Description
env:Receiver ter:CapabilityViolated ter:MaxAreas	<i>There is not enough space to add the new area, see the MaxAreas capability</i>
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>

### 5.3.7 SetArea command

This method is used to synchronize an area in a client with the device.

If an area with the specified token does not exist in the device, the area is created. If an area with the specified token exists, then the area is modified.

A call to this method takes an Area structure as input parameter. The token field of the Area structure shall not be empty.

A device that signals support for the ClientSuppliedTokenSupported capability shall implement this command.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 18 – SetArea command**

SetArea		Access Class: WRITE_SYSTEM
Message name	Description	
SetAreaRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>"Area": Area item to create or modify</li> </ul> tac:Area <b>Area [1][1]</b>	
SetAreaResponse	<i>This message shall be empty</i>	
Fault codes	Description	
env:Receiver ter:CapabilityViolated ter:ClientSuppliedTokenSupported	<i>The device does not support that the client supplies the token</i>	
env:Receiver ter:CapabilityViolated ter:MaxAreas	<i>There is not enough space to add new area, see the MaxAreas capability</i>	
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>	

### 5.3.8 ModifyArea command

This operation modifies the specified area.

The token of the area to modify is specified in the token field of the Area structure and shall not be empty. All other fields in the structure shall overwrite the fields in the specified area.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 19 – ModifyArea command**

<b>ModifyArea</b>		Access Class: WRITE_SYSTEM
<b>Message name</b>	<b>Description</b>	
ModifyAreaRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>• "Area": Area item to modify</li> </ul> tac:Area <b>Area [1][1]</b>	
ModifyAreaResponse	<i>This message shall be empty</i>	
<b>Fault codes</b>	<b>Description</b>	
env:Receiver ter:CapabilityViolated ter:OccupancyControlSupported	<i>An OccupancyControl structure was passed in the request although occupancy control is not supported by this device.</i>	
env:Receiver ter:CapabilityViolated ter:AntipassbackSupported	<i>An Antipassback structure was passed in the request although anti-passback is not supported by this device.</i>	
env:Sender ter:InvalidArgVal ter:NotFound	<i>Area token is not found.</i>	
env:Sender ter:InvalidArgVal ter:ReferenceNotFound	<i>A referred entity token is not found (some devices may not validate referred entities).</i>	

### 5.3.9 DeleteArea command

This operation deletes the specified area.

If it is associated with one or more entities some devices may not be able to delete the area, and consequently a ReferenceInUse fault shall be generated.

If no token was specified in the request, the device shall return InvalidArgs as a generic fault code.

**Table 20 – DeleteArea command**

<b>DeleteArea</b>		Access Class: WRITE_SYSTEM
<b>Message name</b>	<b>Description</b>	
DeleteAreaRequest	<i>This message contains:</i> <ul style="list-style-type: none"> <li>• "Token": Token of Area item to delete.</li> </ul> pt:ReferenceToken <b>Token [1][1]</b>	
DeleteAreaResponse	<i>This message shall be empty</i>	



Fault codes	Description
env:Sender ter:InvalidArgVal ter:NotFound	<i>Area token is not found.</i>
env:Sender ter:InvalidArgVal ter:ReferenceInUse	<i>Failed to delete, the area token is in use</i>

## 5.4 Access point status

### 5.4.1 General

The state of the access point is determined by a number of operations that can be performed on it depending on its capabilities (please refer to access point capabilities in section 5.2).

### 5.4.2 Data structures

#### 5.4.2.1 AccessPointState

The AccessPointState contains state information for an access point. A device shall provide the following fields for each access point instance:

- **Enabled**

Indicates that the access point is enabled. By default this field value shall be True, if the DisableAccessPoint capabilities is not supported.

#### 5.4.3 GetAccessPointState command

This operation requests the AccessPointState for the access point instance specified by the token.

**Table 21 – GetAccessPointState command**

GetAccessPointState		Access Class: READ_SYSTEM_SENSITIVE
Message name	Description	
GetAccessPointStateRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>• <i>"Token": Token of AccessPoint instance to get AccessPointState for.</i></li> </ul> <p>pt:ReferenceToken <b>Token [1][1]</b></p>	
GetAccessPointStateResponse	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>• <i>"AccessPointState": AccessPointState item.</i></li> </ul> <p>tac:AccessPointState <b>AccessPointState [1][1]</b></p>	
Fault codes	Description	
env:Sender ter:InvalidArgVal ter:NotFound	<i>AccessPoint is not found</i>	

## 5.5 Access control commands

### 5.5.1 General

The service control commands contain operations that allow modifying access point states and controlling access points.

### 5.5.2 Data structures

#### 5.5.2.1 Enumeration: Decision

The Decision enumeration represents a choice of two available options for an access request:

- **Granted**  
The decision is to grant access.
- **Denied**  
The decision is to deny access.

#### 5.5.3 EnableAccessPoint command

This operation allows enabling an access point.

A device that signals support for DisableAccessPoint capability for a particular access point instance shall implement this command.

**Table 22 – EnableAccessPoint command**

EnableAccessPoint		Access Class: ACTUATE
Message name	Description	
EnableAccessPointRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li>• <i>"Token": Token of the AccessPoint instance to enable.</i></li> </ul> <p>pt:ReferenceToken <b>Token [1][1]</b></p>	
EnableAccessPointResponse	<i>This message shall be empty</i>	
Fault codes	Description	
env:Sender ter:InvalidArgVal ter:NotFound	<i>The specified token is not found.</i>	
env:Receiver ter:ActionNotSupported ter:NotSupported	<i>The operation is not supported.</i>	

#### 5.5.4 DisableAccessPoint command

This operation allows disabling an access point.

A device that signals support for the DisableAccessPoint capability for a particular access point instance shall implement this command.

**Table 23 – DisableAccessPoint command**

<b>DisableAccessPoint</b>		Access Class: ACTUATE
<b>Message name</b>	<b>Description</b>	
DisableAccessPointRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li><i>"Token": Token of the AccessPoint instance to disable.</i></li> </ul> <p>pt:ReferenceToken <b>Token [1][1]</b></p>	
DisableAccessPointResponse	<i>This message shall be empty</i>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgVal ter:NotFound	<i>The specified token is not found.</i>	
env:Receiver ter:ActionNotSupported ter:NotSupported	<i>The operation is not supported.</i>	

### 5.5.5 ExternalAuthorization command

This operation allows to deny or grant decision at an access point instance.

A device that signals support for ExternalAuthorization capability for a particular access point instance shall implement this method.

**Table 24 – ExternalAuthorization command**

<b>ExternalAuthorization</b>		Access Class: ACTUATE
<b>Message name</b>	<b>Description</b>	
ExternalAuthorizationRequest	<p><i>This message contains:</i></p> <ul style="list-style-type: none"> <li><i>"AccessPointToken": Token of the AccessPoint instance.</i></li> <li><i>"CredentialToken": Optional token of the Credential involved.</i></li> <li><i>"Reason": Optional reason for decision.</i></li> <li><i>"Decision": Decision - Granted or Denied.</i></li> </ul> <p>pt:ReferenceToken <b>AccessPointToken [1][1]</b>  pt:ReferenceToken <b>CredentialToken [0][1]</b>  xs:string <b>Reason [0][1]</b>  tac:Decision <b>Decision [1][1]</b>  <i>(extendable)</i></p>	
ExternalAuthorizationResponse	<i>This message shall be empty</i>	
<b>Fault codes</b>	<b>Description</b>	
env:Sender ter:InvalidArgVal ter:NotFound	<i>AccessPoint is not found.</i>	
env:Receiver ter:ActionNotSupported ter:NotSupported	<i>The operation is not supported.</i>	

## 6 Notification topics

### 6.1 General

This section defines notification topics specific to the access control service.

### 6.2 Event overview

#### 6.2.1 General

The access control service specifies events to be used for access transactions, for example an access request is made and an access is granted or denied, when duress is detected, and when an important configuration has been changed.

The main topics for access transaction events are:

- tns1:AccessControl/AccessGranted/ - when access is granted.
- tns1:AccessControl/AccessTaken/ - when access is taken after being granted.
- tns1:AccessControl/AccessNotTaken/ - when access is not taken after being granted.
- tns1:AccessControl/Denied/ - when access is denied.
- tns1:AccessControl/Duress - when duress is detected.
- tns1:AccessControl/Request/ - when external authorization is requested or has timed out.

The main topic for status updates is:

- tns1:AccessPoint/State/ - for status updates.

The main topics for configuration change notifications are:

- tns1:Configuration/AccessPoint - when access point configuration has been changed.
- tns1:Configuration/Area - when area configuration has been changed.

Note that the term “main topic” here means that a client may subscribe to e.g. tns1:AccessControl/AccessGranted, but the actual event sent (and thus received) may be the main topic itself or any subtopic of the main topic (such as tns1:AccessControl/AccessGranted/Credential). New subtopics may be defined in the future.

#### 6.2.2 General transaction event layout

All transaction events use the following message scheme:

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                             Type="pt:ReferenceToken" />
  </tt:Source>
  <tt>Data>
    <tt:SimpleItemDescription Name="External"
                             Type="xs:boolean" />
    <tt:SimpleItemDescription Name="CredentialToken"
                             Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                             Type="xs:string" />
    <tt:SimpleItemDescription Name="Reason"
                             Type="xs:string" />
  </tt>Data>
</tt:MessageDescription>
```

where AccessPointToken identifies the access point where the decision was made.

The Data parameters are optional. See the definitions in the following sections for their requirements. The parameter CredentialToken shall be present and CredentialHolderName may

be present for credential based transactions. The optional parameter Reason holds error reason information and the optional parameter External signals whether the transaction was triggered as a result of the ExternalAuthorization command.

## 6.3 Access granted

### 6.3.1 General

Whenever a positive access decision is made, i.e., access is granted, the device shall provide a corresponding event message as per the following sub-sections.

The event shall be sent immediately once the decision is made regardless of whether access was taken or not.

### 6.3.2 Anonymous

Whenever access is granted for an anonymous user at an access point, a device that signals AnonymousAccess capability for a particular access point instance shall provide the following event:

Topic: tns1:AccessControl/AccessGranted/Anonymous

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="External"
                              Type="xs:boolean" />
  </tt:Data>
</tt:MessageDescription>
```

If the command was triggered as a result of the ExternalAuthorization command, the data element External shall be set to true, otherwise the element is optional.

### 6.3.3 Credential

Whenever a valid credential has passed all the necessary checks and a user or card holder is granted access to the access point, but not yet accessed it (entered or exited), the device shall provide the following event data:

Topic: tns1:AccessControl/AccessGranted/Credential

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="External"
                              Type="xs:boolean" />
    <tt:SimpleItemDescription Name="CredentialToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="SecurityLevelToken"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="ExemptedAccess"
                              Type="xs:boolean" />
  </tt:Data>
</tt:MessageDescription>
```

If the command was triggered as a result of the ExternalAuthorization command, the data element External shall be set to true, otherwise the element is optional.

The data elements CredentialHolderName, SecurityLevelToken and ExemptedAccess are optional.

## 6.4 Access taken

### 6.4.1 General

A device that signals support for AccessTaken capability for a particular access point instance shall provide a corresponding event to notify client whenever an authorized person takes access.

### 6.4.2 Anonymous

A device that signals support for AnonymousAccess capability for a particular access point instance shall provide the following event:

Topic: tns1:AccessControl/AccessTaken/Anonymous

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

### 6.4.3 Credential

When the device detects that access is taken and the credential can be identified, it shall provide the following event:

Topic: tns1:AccessControl/AccessTaken/Credential

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt>Data>
    <tt:SimpleItemDescription Name="CredentialToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                              Type="xs:string" />
  </tt>Data>
</tt:MessageDescription>
```

The data element CredentialHolderName is optional.

## 6.5 Access not taken

### 6.5.1 General

A device that signals support for AccessTaken capability for a particular access point instance shall provide a corresponding event to notify client whenever a person was authorized but did not take access in time.

### 6.5.2 Anonymous

A device that signals support for AnonymousAccess capability for a particular access point instance shall provide the following event:

Topic: tns1:AccessControl/AccessNotTaken/Anonymous

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

### 6.5.3 Credential

When the device detects that access is not taken and the credential can be identified, it shall provide the following event:

```
Topic: tns1:AccessControl/AccessNotTaken/Credential

<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                             Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="CredentialToken"
                             Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                             Type="xs:string" />
  </tt:Data>
</tt:MessageDescription>
```

The data element CredentialHolderName is optional.

## 6.6 Access denied

### 6.6.1 General

The device shall provide one of the events as per the following sub-sections whenever a person is denied to access. The following applies to all subsections:

Even if there are multiple reasons for denial, a device shall only send one reason and how the device chooses the reason in this case is outside the scope of this standard. The denial reason shall be present in the parameter Reason.

If the denial reason is due to the credential being disabled (CredentialNotEnabled, CredentialNotActive or CredentialExpired) more detailed information about the reason of disabling the credential can be found in the credential itself.

The following strings shall be used for the reason field:

- **CredentialNotEnabled**  
The device shall provide this reason whenever a valid credential is not enabled or has been disabled, e.g. due to credential being lost etc., to prevent unauthorized entry.
- **CredentialNotActive**  
The device shall provide this reason whenever a valid credential is presented though it is not active yet, e.g. the credential was presented before the start date.
- **CredentialExpired**  
The device shall provide this reason whenever a valid credential was presented after its expiry date.
- **InvalidPIN**  
The device shall provide this reason whenever an entered PIN code does not match the credential.
- **NotPermittedAtThisTime**  
The device shall provide this reason whenever a valid credential is denied access to the requested access point because the credential is not permitted at the moment.
- **Unauthorized**  
The device shall provide this reason whenever the presented credential is not authorized.

- **Other**

The device shall provide this reason whenever the request is denied and no other specific event matches it or is supported by the service.

More values may be defined by either future revisions of this specification or as vendor specific extensions. To allow for this, a client shall treat unknown strings as “Other”.

While the Reason strings originally defined by this standard do not use a QName style syntax, extensions to the Reason values will always use a QName style syntax. The prefix “pt” is reserved for use by ONVIF, i.e. “pt:<reason>”. Vendor specific extensions should choose a suitable prefix.

Current extensions are:

- **pt:InvalidIdentifierValue**

The device shall provide this reason whenever an entered second recognition method (such as a fingerprint or a second credential identifier), does not match the initial credential identifier.

### 6.6.2 Anonymous

The device that signals support for the AnonymousAccess capability for a particular access point instance shall provide the following event when access is denied and credential information is not provided:

Topic: tns1:AccessControl/Denied/Anonymous

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                             Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="External"
                             Type="xs:boolean" />
    <tt:SimpleItemDescription Name="Reason"
                             Type="xs:string" />
  </tt:Data>
</tt:MessageDescription>
```

If the command was triggered as a result of the ExternalAuthorization command, the data element External shall be set to true, otherwise the element is optional.



### 6.6.3 Credential

When the device denies access and the credential can be identified, it shall provide the following event:

Topic: tns1:AccessControl/Denied/Credential

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="External"
                              Type="xs:boolean" />
    <tt:SimpleItemDescription Name="CredentialToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="SecurityLevelToken"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="Reason"
                              Type="xs:string" />
  </tt:Data>
</tt:MessageDescription>
```

If the command was triggered as a result of the ExternalAuthorization command, the data element External shall be set to true, otherwise the element is optional.

The data element CredentialHolderName and SecurityLevelToken are optional.

### 6.6.4 CredentialNotFound

Under some circumstances a device may be not able to resolve authentication data to a credential token.

Whenever there is no credential matching the request stored in the device, the device shall provide the following event:

Topic: tns1:AccessControl/Denied/CredentialNotFound

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="IdentifierType"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="IdentifierValue"
                              Type="xs:hexBinary" />
  </tt:Data>
</tt:MessageDescription>
```

The content of the Identifier type string must be one of the formats listed in the Credential Specification (e.g. pt:Card) or a vendor-specific string.

The content of the Identifier value string must the contain credential number, PIN or any other string identifying the credential that could not be found.

#### 6.6.4.1 Card

Please note that the use of this event is provided for backward compatibility reasons. See also `CredentialNotFound`.

Whenever there is no credential matching the request stored in the device, the device shall provide the following event:

Topic: `tnsl:AccessControl/Denied/CredentialNotFound/Card`

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt>Data>
    <tt:SimpleItemDescription Name="Card"
                              Type="xs:string" />
  </tt>Data>
</tt:MessageDescription>
```

The content of the Card string is vendor specific. It may contain the complete identification string of the card, part of this information or remain empty.

### 6.7 Duress

A device that signals support for the Duress capability for a particular access point instance shall provide the following event whenever a condition of duress is detected.

Topic: `tnsl:AccessControl/Duress`

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt>Data>
    <tt:SimpleItemDescription Name="CredentialToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                              Type="xs:string" />
    <tt:SimpleItemDescription Name="Reason"
                              Type="xs:string" />
  </tt>Data>
</tt:MessageDescription>
```

The data parameters `CredentialToken` and `CredentialHolderName` are optional and may be omitted for anonymous access.

## 6.8 External authorization

### 6.8.1 General

A device that signals support for `ExternalAuthorization` capability for a particular access point instance shall provide events defined in this section whenever it requests for external authorization. These notification messages shall be used in conjunction with corresponding access control service operations which provide feedback to the device.

### 6.8.2 Anonymous

Whenever a device that signals `AnonymousAccess` capability for particular access point instance requests external agent to authorize a person when credential information is not

available, e.g. when a REX button has been pressed and operator's confirmation is needed, it shall provide the following event:

Topic: tns1:AccessControl/Request/Anonymous

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

### 6.8.3 Credential

Whenever the device requests external agent to authorize a person, the device shall send the following event:

Topic: tns1:AccessControl/Request/Credential

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt>Data>
    <tt:SimpleItemDescription Name="CredentialToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="CredentialHolderName"
                              Type="xs:string" />
  </tt>Data>
</tt:MessageDescription>
```

CredentialHolderName is optional and may be omitted or an empty string if it cannot be resolved.

### 6.8.4 Timeout

A device shall provide the following event, whenever an external authorization request times out:

Topic: tns1:AccessControl/Request/Timeout

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

### 6.8.5 Example

A client that implements support for external authorization typically listens to the AccessControl/Request/<subtopic> events. When any of these events arrive, they are evaluated. If access is granted or denied, the ExternalAuthorization command is called on the device.

## 6.9 Status changes

### 6.9.1 General

The device shall provide the status change events to inform subscribed clients when PACS entity status is changed. The device shall use the topics defined in this section associated with the respective message description.

### 6.9.2 Access point

The device that signals support for the DisableAccessPoint capability for a particular access point instance shall provide the following event whenever the state, enabled or disabled, of this access point is changed:

Topic: tns1:AccessPoint/State/Enabled

```
<tt:MessageDescription IsProperty="true">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="State"
                              Type="xs:boolean" />
  </tt:Data>
</tt:MessageDescription>
```

### 6.9.3 Security level

If more than one security level is supported by the device (see SupportedSecurityLevels capability), then the device shall be capable of generating the following event whenever the active security level have changed for an access point.

Topic: tns1:AccessPoint/State/SecurityLevel

```
<tt:MessageDescription IsProperty="true">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
  <tt:Data>
    <tt:SimpleItemDescription Name="AuthenticationProfileToken"
                              Type="pt:ReferenceToken" />
    <tt:SimpleItemDescription Name="ActiveSecurityLevelToken"
                              Type="pt:ReferenceToken" />
  </tt:Data>
</tt:MessageDescription>
```

## 6.10 Configuration changes

### 6.10.1 General

Whenever configuration data has been changed, added or been removed the device shall provide these events to inform subscribed clients.

### 6.10.2 Access Point

Whenever important configuration data for an access point is changed or an access point is added, the device shall provide the following event:

Topic: tns1:Configuration/AccessPoint/Changed

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

Whenever an access point is removed, the device shall provide the following event:

Topic: tns1: Configuration/AccessPoint/Removed

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AccessPointToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

### 6.10.3 Area

Whenever configuration data for an area is changed or an area is added, the device shall provide the following event:

Topic: tns1:Configuration/Area/Changed

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AreaToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

Whenever an area is removed, the device shall provide the following event:

Topic: tns1: Configuration/Area/Removed

```
<tt:MessageDescription IsProperty="false">
  <tt:Source>
    <tt:SimpleItemDescription Name="AreaToken"
                              Type="pt:ReferenceToken" />
  </tt:Source>
</tt:MessageDescription>
```

## Annex A. Revision History

Rev.	Date	Editor	Changes
1.0	Apr-2013	Yuri Timenkov	Initial version
1.0.1	Aug-2013	Hans Busch	Change Request 1053
1.0.2	Dec-2013	Michio Hirai	Change Request 1234
1.0.3	Jun-2014	Michio Hirai	Change Request 1363, 1367, 1355, 1357, 1364, 1366, 1347, 1348, 1365
1.1	Jun-2017	Patrik Björning Rygert	Change Request 1803
17.12	Dec-2017	Hiroyuki Sano	Change Request 2170, 2171
18.06	Jun-2018	Patrik Björning Rygert	Change Request 2300 Added support for client-supplied tokens Added full management support for access points Added full management support for areas Added support for authentication behavior